

WiFi Alarm System



- Support "ding dong" doorbell function;
- Zone names can be revised by users;
- Support 100pcs Wireless relay/Wireless Socket;
- Backup battery can enable the wifi continue to work after external power cut
- 10 seconds personal voice message record;
- Can control the system by calling-in: arm, disarm, listening-in etc;
- Colour Options: White & Black;
- Wireless learning coding, compatible with 2262 or 1527 chip sensors;
- Multi-Language: English, Russian, French, Spanish, Svenska, Turk and Dutch;

Specifications

GSM Frequency	850/900/1800/1900Mhz
Backup Battery	For continue working 24 hours when power cut/off
Battery	Lithium battery 3.7V 1000mAh
Display	LCD indicator
Personal Message Record	10s
Input Voltage	DC12V
Standby Current	< 200mA
Alarm Current	< 300mA
Alarm Sound	110dB
Wireless Frequency	433Mhz
Support Wireless Sensors	EV1527/300K, 2262/1.5-4.7M
Wireless Distance	100m open
WiFi	2.4G
GPRS	Support
Support Sensors Quantity	Wireless sensor 100pcs
Work Temperature	-10°C to 40°C

Features & Functions

Working Ways	WiFi / GPRS / GSM
Defence Zones	100 Wireless Zones
	8 Wired Zones
	100pcs wireless power socket or wireless relay
Alarm call and APP user No.	6 groups of call phone number
	6 groups of APP user
Remote control the system	Arm
	Disarm
	Monitor
	Talking
	Control relay open and close (Option)
Basic Functions	LCD indicator Arm/Disarm/Stay arm/Alarm/Signal
	English voice operation instruction
	Multi-Language menu display
	Password protection function
	0-90secs. delay alarm and arm setting
	Stay intelligent arm
	Operating the host by APP
Reset factory setting	



EFFICIENT SYSTEMS PTE LTD

BLK 52, UBI AVE 3, #03-42 FRONTIER, SINGAPORE 408867

TEL: +65 68582880 FAX: +65 67435906

www.efficient.com.sg